

- Trasmettitori di velocità dell'aria
- Trasmettitori di velocità e temperatura dell'aria
- Trasmettitori di velocità, temperatura e umidità relativa dell'aria
- Trasmettitori di velocità dell'aria a filo caldo
- Air speed transmitter
- Temperature, Air speed transmitters
- Temperature, Relative Humidity and Air speed transmitters
- Hotwire Air speed transmitters



### **HD103T.0 Active Air speed transmitter**

The HD103T.0 measures air speed by using an omnidirectional hotwire probe. It has three configurable analogue outputs: 4...20mA and 0...20mA current outputs and 0...10Vdc voltage output (0...1Vdc or 0...5Vdc outputs can be supplied on request). The output can be chosen by using the jumpers inside the instrument.

The sensor set on the top of the probe is very delicate and must be protected with the special frame provided with the instrument. During transportation, the sensor is closed into a cylinder screwed on the top of the probe; during installation, unscrew this cylinder and screw the protective cover in its place.

Technical specifications		Notes
Air speed Measuring range	0.055m/s	
Air speed Accuracy range 00.99m/s range 15m/s	±0.04m/s ±0.2m/s	at 50%RH and 1013hPa
Temperature measuring range	-20+80°C	
Temperature Accuracy range 070°C remaining range	±0.3°C ±0.4°C	
Output (for both temperature and air speed)	420mA 020mA 010Vdc	05Vdc and 01Vdc outputs on request
Load resistance	$R_L < 500\Omega$ $R_L > 100k\Omega$	for current outputs for voltage outputs
Power supply	24Vac ±10%, 5060Hz	110Vac or 230Vac on request
Operating temperature electronics probe	-5+50°C -20+80°C	
Compensation temperature	0+80°C	
Storage temperature	-10+80°C	
Electronics protection class	IP67	
Sensor working conditions	Clean air, RH<90%	
Case dimensions	120 x 80 x 55	Without probe
Probe cable length	L=5m	

### Installation notes

- Select the air speed and temperature **output** by using the jumpers set on the board.
- The probe must be used with clean air only and humidity below 90%.
- The transmitters are factory calibrated and no further adjustments are required.
- Each instrument is calibrated with its probe. Don't mix up the probes and instruments: the calibration will have to be repeated.


# Electrical connections

Power supply

Power the instrument at the voltage shown in the electrical specifications.

Analogue output

The output signal comes from m/s and GND terminals for air speed, from °C and GND for temperature.





#### ORDERING CODES


HD103T.0: Active air speed and temperature transmitter. Analogue outputs: 4...20mA, 0...20mA and 0...10Vdc selected by jumper. Omnidirectional probe with wired protective cover  $\varnothing$ =80mm connected to the electronics through a 5-metre cable. Air speed range 0...5m/s. Temperature output range -20...+80°C. Power supply 24Vac (115 and 230Vac on request). Probe operating temperature -20°...+80°C, electronics operating temperature -5...+50°C.













Costruzione strumenti di misura portatili e da tavolo Trasmettitori a loop di corrente o tensione Temperatura - Umidità - Pressione Velocità dell'aria - Luce - Acustica pH - Conducibilità - Ossigeno disciolto - Torbidità Elementi per stazioni meteo

Manufacture of portable and bench top instruments Current and voltage loop transmitters Temperature - Humidity - Pressure Air speed - Light - Acoustics pH - Conductivity - Dissolved Oxygen - Turbidity Elements for weather stations



### CENTRO DI TARATURA SIT N.124

Temperatura - Umidità - Pressione - Acustica - Fotometria/Radiometria

# SIT CENTRE N°124

Temperature - Humidity - Pressure - Photometry/Radiometry - Acoustics









